

## Linksys IP Phone Setup with The Tpad Global Network

1. Connect the Power Supply Cable and then Network Cable from your Internet connection to the **LAN** Port on the Phone.
2. After the unit has powered up, press MENU > NETWORK > CURRENT IP. This will show you the IP address of the phone.
3. Open your Internet Explorer / Firefox and type the IP address:  
e.g. <http://192.168.2.1> and press **Enter**
4. Click on **Admin Login**.



**SIPURA**  
technology, inc.

Sipura Telephone Configuration

Info System User [Admin Login](#) [basic](#) | [advanced](#)  
[Personal Directory](#) [Call History](#)

**System Information**

DHCP:	Enabled	Current IP:	192.168.2.3
Host Name:	SipuraSPA	Domain:	Belkin
Current Netmask:	255.255.255.0	Current Gateway:	192.168.2.1
Primary DNS:	192.168.2.1		
Secondary DNS:			

**Product Information**

Product Name:	SPA-921	Serial Number:	4MJ00G800945
Software Version:	4.1.10(b)	Hardware Version:	1.0.0(0458)
MAC Address:	000E08DF06DB	Client Certificate:	Installed
Licenses:	None		

**Phone Status**

Current Time:	1/1/2003 12:02:22	Elapsed Time:	00:02:22
Broadcast Pkts Sent:	4	Broadcast Bytes Sent:	1368
Broadcast Pkts Recv:	6	Broadcast Bytes Recv:	1111
Broadcast Pkts Dropped:	0	Broadcast Bytes Dropped:	0
RTP Packets Sent:	0	RTP Bytes Sent:	0
RTP Packets Recv:	0	RTP Bytes Recv:	0

5. Then click on **Ext 1**

**SIPURA**  
technology, inc.

Sipura Telephone Configuration

Info System SIP Regional Phone **Ext 1** User

User Login basic | advanced  
Personal Directory Call History

**General**  
Line Enable: yes

**NAT Settings**  
NAT Mapping Enable: no NAT Keep Alive Enable: no

**SIP Settings**  
SIP Port: 5060 SIP Debug Option: none

**Call Feature Settings**  
Message Waiting: no Default Ring: 1  
Mailbox ID:

**Proxy and Registration**  
Proxy: sip.tpad.com Register: yes  
Make Call Without Reg: no Register Expires: 3600  
Ans Call Without Reg: no

**Subscriber Information**  
Display Name: John Smith User ID: 1123444  
Password: mypass Use Auth ID: yes  
Auth ID: 1123444

**Audio Configuration**  
Preferred Codec: G711u Use Pref Codec Only: no  
Silence Supp Enable: no DTMF Tx Method: Auto

Undo All Changes Submit All Changes

Set the values as follows:

- **Proxy to: sip.tpad.com**
- **Display name to your name**
- **Password to your Tpad account password**
- **Auth ID to your Tpad phone number e.g. 1123444**
- **User ID to your Tpad phone number e.g. 1123444**
- **Use Auth ID to yes**

Click **Submit All Changes**

The phone will restart and register with Tpad.