

Pirelli LP-D10 GSM/VoIP Phone with Tpad



This guide covers:

- Setting up your Tpad account on the Pirelli LP-D10
- Making Calls with Tpad
- Configuring your Wireless LAN access point on the LP-D10

Setting up your Tpad account on the Pirelli LP-D10

Press **Menu** > **WLAN** > **SIP Settings**.

To configure the phone with Tpad you need to define the following settings in the **SIP Settings** menu:

Username	Your Tpad phone number e.g. 1123444
Password	Your Tpad account password.
Auth. name	Your Tpad phone number e.g. 1123444 .
Domain name	Enter sip.tpad.com
Local port	Enter 5060 .
Proxy server	Enter sip.tpad.com .
Proxy port	Enter 5060
Register server	Enter sip.tpad.com .
Register port	Enter 5060
Register period	Enter 3600
Outbound server	Enter sip.tpad.com
Outbound port	Enter 5060
RTP audio port	Enter 9000
RTP pkt.period	Enter 20
Preferred codec	Select G.711A

Press **back** three times to return to the home screen.

Making calls with Tpad

To make a normal GSM phone call when Tpad is not active, key in the phone number, including the area code and press the **Green key** to call the number. Press the **Red key** to end a call or to cancel the call attempt .

When Tpad Mode is active, the next outgoing call will go out via Tpad by default.

You can press the **Left soft key > Options** to select whether to send the call by GSM or Tpad WLAN



Configuring your Wireless LAN access point on the LP-D10

Select WLAN Profile

Before you set the access to WLAN network, select a profile, and check if the profile is set and active.

1. Press **Menu** > WLAN > WLAN Settings > Active Settings

Choose an appropriate profile:

- **Home**: when you set a WLAN in house, use this profile and save the Home WLAN info.
- **Office**: when you set a WLAN in office, use this profile and save the Office-WLAN info.
- **Hotspot**: Set the WLAN in the Hotspot when you have the operator of the Hotspot.

Define your WLAN access point

- a) Set SSID by site survey

1. Press **Menu** > **WLAN** > **WLAN settings** > **Edit act. settings** > **SSID & security** > **SSID** > **Site survey**. The display shows a list of all APs which are found nearby with good signal strength.
2. Select your WLAN access points AP's SSID

- b) Set SSID manually

1. Press **Menu** > **WLAN** > **WLAN settings** > **Edit act. settings** > **SSID & security** > **SSID** > **Manual**. Input SSID in the SSID edit window.

- **Security Setting**: for WLAN encryption:

- a) Set security

1. Press **Menu** > **WLAN** > **WLAN settings** > **Edit act. settings** > **SSID & security** > **SSID** > **Security**. The display shows the security items to be set.

- **Open** := It sets no encryption.
- **WEP** := WEP encryption, for WEP key settings. The key must be entered in hexadecimal or ASCII format: A-F and 0-9. On the right top corner, a counter decrements and reaches zero as all characters have been entered